
3400

Male connector BSPT thraed





| CODE | Т | ØOD | L | S | Н1 | H2 | GR. |
|------------|-------|-----|------|------|----|----|-------|
| 3400TR184 | R1/8" | 4 | 17,0 | 7,0 | 10 | 10 | - |
| 3400TR144 | R1/4" | 4 | 20,0 | 9,5 | 14 | 10 | - |
| 3400TR186 | R1/8" | 6 | 18,0 | 7,5 | 11 | 13 | 18,0 |
| 3400TR146 | R1/4" | 6 | 18,0 | 7,5 | 14 | 13 | 25,0 |
| 3400TR386 | R3/8" | 6 | 19,0 | 8,5 | 17 | 13 | - |
| 3400TR188 | R1/8" | 8 | 19,5 | 7,0 | 13 | 14 | 22,0 |
| 3400TR148 | R1/4" | 8 | 19,5 | 7,0 | 14 | 14 | 27,0 |
| 3400TR388 | R3/8" | 8 | 20,5 | 8,0 | 17 | 14 | 33,0 |
| 3400TR1810 | R1/8" | 10 | 24,0 | 9,0 | 17 | 19 | - |
| 3400TR1410 | R1/4" | 10 | 24,0 | 9,0 | 17 | 19 | 48,0 |
| 3400TR3810 | R3/8" | 10 | 24,0 | 9,0 | 17 | 19 | 49,0 |
| 3400TR1210 | R1/2" | 10 | 25,0 | 10,0 | 22 | 19 | 67,0 |
| 3400TR1412 | R1/4" | 12 | 24,0 | 9,0 | 19 | 22 | - |
| 3400TR3812 | R3/8" | 12 | 24,0 | 9,0 | 19 | 22 | - |
| 3400TR1212 | R1/2" | 12 | 25,0 | 10,0 | 22 | 22 | - |
| 3400TR1414 | R1/4" | 14 | 26,0 | 10,5 | 22 | 24 | - |
| 3400TR3814 | R3/8" | 14 | 25,0 | 8,0 | 22 | 24 | 70,0 |
| 3400TR1214 | R1/2" | 14 | 26,0 | 9,0 | 22 | 24 | 80,0 |
| 3400TR1216 | R1/2" | 16 | 27,0 | 9,5 | 24 | 27 | 101,0 |
| 3400TR3416 | R3/4" | 16 | 28,0 | 10,5 | 27 | 27 | |
| 3400TR1218 | R1/2" | 18 | 30,0 | 10,5 | 27 | 30 | 132,0 |
| 3400TR3418 | R3/4" | 18 | 30,0 | 10,5 | 27 | 30 | 143,0 |
| 3400TR1220 | R1/2" | 20 | 32,0 | 11,0 | 30 | 32 | - |
| 3400TR3420 | R3/4" | 20 | 32,0 | 11,0 | 30 | 32 | - |
| 3400TR1222 | R1/2" | 22 | 33,0 | 11,0 | 32 | 36 | - |
| 3400TR3422 | R3/4" | 22 | 33,0 | 11,0 | 32 | 36 | 195,0 |
| 3400TR122 | R1" | 22 | 33,0 | 11,0 | 36 | 36 | 225,0 |
| 3400TR128 | R1" | 28 | 36,0 | 11,0 | 41 | 42 | - |